

Lightning Shutdown

1. Complete “End of Normal Night of Observing” shutdown
2. In Dome
 - Turn off all instrument electronics, including the camera shutter, and unplug from orange outlets under scope (Four Cables)
 - If in use: shut down laptop computer, and unplug laptop and monitor from the orange UPS outlets located near the floor on the platform control console.
 - Turn off TCS computer using the light switch
 - Turn off telescope power
 - Lower platform
 - Turn off main power
3. In Control room
 - On BIGAUX double click “shutdown bigpop”, and click shutdown bigpop when prompted
 - Manually shutdown all computers.
 - Gerard
 - BIGCCD
 - Bigguider
 - BIGAUX
 - Turn off printer.
 - Turn off Telcom server
 - Turn off and unplug power strip on west wall.
 - Unplug printer relay.
 - Unplug everything from orange outlets behind observer work station, as well as UPS outlets by the video finder scope monitor
 - Unplug computer racks (plugged into orange outlet #4 on wall below emergency stop)
4. In UPS Room, unplug:
 - GPS
 - Emergency Stop Power 110 VAC
 - Shutdown UPS following instructions posted on board.

From:

<https://lavinia.as.arizona.edu/~tscopewiki/> - MOON

Permanent link:

https://lavinia.as.arizona.edu/~tscopewiki/doku.php?id=kuiper:lightning_shutdown&rev=1512169279

Last update: **2017/12/01 16:01**

