# Schulman Telescope Startup Procedure

1/17

Updated 8/4/2022 - Travis Deyoe

The order of operations below is designed for time efficiency. Missing a step could lead to frustration as some steps may feel "out of order" but are designed to reduce down time waiting for things to power on.

### **Pre-Startup Checks**

#### **Pull Off Tarps**

The Telescope, Controller, and desk will always be tarped whenever the telescope is put into Lightning Shutdown. They will need to be removed before inspecting or moving the telescope.

Perform your best interpretive dance to appease the tarp gods. If that does not make the tarp fall off you must remove it manually. Folding it up and placing it to the right of the brown cabinet is a nice touch.

#### **Check Telescope Position**

Verify the telescope is not at any limits. If it is or looks "wrong" to you, move it manually into a safe position before the next steps. This guarantees that it will be able to successfully and safely home in a future step. It's recommended to place it either at Zenith or the Park position.

#### **Check Emergency Stops**

If engaged, release any E-stops on the Hand Paddle, Telescope Controller, and the MaxDome Controller by pulling them outward. They all appear as big red buttons that scream "PRESS ME IN CASE OF EMERGENCY".



#### **Check the Telescope Balance State**

The telescope is in a balanced state when one of the following conditions are met:

- The camera is on with a single weight attached at the "top" of the backplate.
- The focuser is on with both eyepiece weights attached on either side of the focuser and there is no weight on the "top" of the telescope.

In either state an eyepiece should be in the 6" refractor and the mirror covers are open (this will be done later in this step). If the telescope is in neither of these states, then placeit in one of the Configurations now or at the very least before homing the telescope.

#### Check RA Encoder Tape

Follow the RA optical tape along the big RA wheel and check for any smudges, bug guts, and so forth. The WEST read head is active while the east read head is not currently utilized, so make sure through the entire motion of the telescope (in RA of course) that there is nothing blocking the reading of the tape on the west side and that there is nothing obstructing the read head's ability to "see" the optical tape.

Make certain both the drive and idler bearings are also free of anything that might be transferred to the optical tape. A bit of felt is held in place there that *should* wipe off anything, but its best to check still.

If anything is observed, use a microfiber cloth or TEX wipe to wipe it away. You can use 99% isopropyl alcohol if necessary. Note that you should only wipe along the narrow width NOT along the circumference (or length) of the tape.

## **Powering Everything On**

Now that you have inspected the telescope for safety, it is now time to start turning things on.

### Power On UPS's

First plug in the big and small UPS's to the left of the desk. The big UPS should be twisted clockwise after insertion in order to secure it in the socket. The big UPS powers the larger controller box on the wall above it, while the small UPS powers basically everything else.





Next you must turn on both UPS's. Press and hold the corresponding "on" button for at least a second until you hear a beep, then let go. For the big UPS this will take a few moments as it cycles through some littles (shown in full in the GIF below). The small UPS will power on quicker.



Both UPS's will immediately supply power to their output plugs, so no further button pressing is

#### necessary.

#### Power On Controller and Desktop Computer

The big gray box on the wall is the Controller. Turn it on by turning the large red switch on the bottom left of the Controller box to the right (clockwise). Assuming the UPS was powered on in the last step, fans and other noises will be heard as the system comes on.



Now is also when you should turn on the desktop computer. It is under the desk behind the little door on the left. The power button is the same color as the computer case so in a dimly lit room (like it most likely is now without the dome open) you may need a light to find it.

#### **Power on TIM Unit**

The TIM unit is a small gray/black box on back of the telescope just below where the camera or eyepiece is installed. There is a standard power switch on the left side to turn it on.

#### **Check Controller Ethernet Cable**

While the Controller and desktop computer are powering on (the Controller takes about 15 years to do so), go into the warm room. Now go into the closet. There is a gray ethernet cable labelled "Controller." Plug this into the switch on the right wall and confirm there are happy internet lights on the switch.

2025/07/11 01:53





### **Desktop Tasks**

Procced back to the desktop computer which should be fully powered on. Login to the computer (standard SkyCenter password). The next few task will all be done on this computer.

#### **Open Mirror Covers**

Open the RCOS TIM software from the desktop link or toolbar quick link.



Connect to the TIM unit and navigate to the "Primary Mirror Covers" tab.

rimary Mirror Cover Controll		
Cover 1	Cover 2	Open
0% 1 mA	0 mA	X Reset
Cover 3	Cover 4	Close
0% 1 mA	0% 1 mA	

Open the Mirror Covers:

connect	Record	Focuser	Rotator Fan Tem	perature Pri	. Mirror Cover
rimary M	firror Cover (	Controller			
Cover	1		Cover 2		Open
101	0%	1 mA		0% 1 mA	X Reset
Cover	3		Cover 4		Close
	0%	0 mA		0% 1 mA	

If the mirror covers aren't opening correctly or the current stays high (over 1000milliamps) then there is a problem. Abort the opening (or closing) and follow this procedure

#### Remotely connect to MIC and PubSub

Launch VNC Viewer. It will appear on the middle right of the desktop (or just search it in the start menu). You will now want to remotely connect to the MIC and PubSub computers that run the Controller. This is what VNC Viewer does so just double click on the MIC and SUBSUB links in VNC Viewer and it will open a window of each.

Last update: 2022/09/14 public:catalinas:lemmon:schulman\_32:startup\_procedure.https://lavinia.as.arizona.edu/~tscopewiki/doku.php?id=public:catalinas:lemmon:schulman\_32:startup\_procedure&rev=1663191401



#### Verify MIC and PubSub time

#### NOTE: At this time PubSub is dumb and will display a "Logout" screen. Click that button and it will display an empty desktop. To find the actual desktop you will need to use the file manager in the Programs menu (top left of the screen)

Make it so you can view the top right of both screens next to each other and confirm that the two computers times are within about 5 seconds of each other. If they are not you must perform the following task: Sync Controller Times.

#### Launch Pubsub software

Initially the desktop will be blank (black). Start PubSub processes by pressing the tool utility icon at the top of desktop. It is circled in the image below:



This will clear the database and give everything a clean start. Eventually (a few minutes) the "JADE" agent will load and the desktop will look like the below:



11/17

The small icons to the right of processes can be pressed to expand them and reveal the list as shown. Once the "Instruments-xx01\_0m8a\_doma" process is loaded under its section PubSub is ready to communicate with the telescope (and the user). The "RPC\_Gateway" process will not show up until communication to PubSub through the web browser commences. This is in the next step. It is OK to close the VNC window.

From Pubsubs Desktop folder double click on the "Clear and Restart Pubsub" program. This will open both a Terminal window and a GUI. The gui will slowly populate with a list of items. **Do not process until all those below show up** 

- Main-Container
- Observatory\_doma\_tus
- Site\_tus

2025/07/11 01:53

- jTCS\_0m8a\_doma\_tus
- Instruments-xx01\_0m8a\_doma
- (RPC\_Gateway) ←- only shows once connected (via this step) to the controller, will not show initially

#### Access the LCOGT (PubSub) GUI

Now that the system is up and running with drives, servos, and PubSub- access the LCOGT GUI:

Last	
update:	nihlisisetalinasilammanischulman 22:startun procedura https://laujnia.as.arizana.edu/_tscapowiki/daku.nhn2id=nuhlisisetalinasilammanischulman 22:startun proceduraErou=1662101/01
2022/09/14	
14.36	

Open Google Chrome and click the bookmark labeled PubSub. You will be presented with the screen below:



The Username is unused so leave it as is or write something funny for the next operator to see. *default* **is** required for the Config File field. Once those are confirmed click OK.

PubSub will now take a long time to load. Go read a book (I recommend Remembrance of Things Past) and come back when you are done. If it feels like it's taking too long try refreshing and logging in again.

2025/07/11 01:53

tus x	<u> </u>					
← → C () pubsub.tus:8080	/gwtpubsub2/#tus/doma/0	)m8a/				Q 🕁 🚺 :
🔢 Apps 😹 PUBSUB! 🕒 APS: Web	Relays 🕒 Power Outlets (Rer	not 🗋 Skycenter Trouble Re:	Mt. Lemmon SkyCent	HANDOUTS SMt. Lemmon	Observar 🌚 Satellite page: RA	P Re 🔤 SDO   Solar Dynamics 🛛 »
Tools ११ Chat (Alan)	tus doma OmBa			TUS	Alive 201	6-11-01 23:21:41 UTC 18:45:10 LST
	+ State Observation Script	Sequencer Source Tracking	Axes Guide Instrument	Ins View Spectrograph Calib	rate Focus Optical Tube Ta	elescope Services 1 Telescope Services 2 🔶
	Tracking		Description		Behaviours	A 10
			Mount Type	1	Astrometric	133
	Disable Roll Disa	ible Pitch Enable Rotator			[not available]	[not available]
	Rotator Mode	acking Loop	Current Message Queue Size		Axes	93
	SICY +		Astrometric	0	Config	18
			[not available]	[not available]	InstrumentSelector	22
	Other States		Axes	0	Monitor	9
	Astrometric Kernel State	Stopped	Config	0	[not available]	[not available]
	Astrometric	Okay	InstrumentSelector	0	Paddle	31
	[not available]	[not available]	Monitor	0	SdbAgent	10
	Container State	Okay	[not available]	[not available]	[not available]	[not available]
	Agent Count	10	Paddle	0	[not available]	[not available]
			SdbAgent	0	[not available]	[not available]
	State		[not available]	[not available]		
	Astrometric	Okay	[not available]	[not available]	Software Repository Path	
	[not available]	[not available]	[not available]	[not available]	Astrometric	issue-5613-2
	Mount	Okay			[not available]	[not available]
	Mount State	Okay	Software Revision		Axes	issue-5613-2
	Config	Okay	Astrometric	3b4d9fe	Config	issue-5613-2
	InstrumentSelector	Окау	[not available]	[not available]	InstrumentSelector	issue-5613-2
	Monitor	Okay	Axes	3b4d9fe	Monitor	issue-5613-2
	[not available]	[not available]	Config	3b4d9fe	[not available]	[not available]
	Paddle	Okay	InstrumentSelector	3b4d9fe	Paddle	issue-5613-2
	SdbAgent	Okay	Monitor	3b4d9fe	SdbAgent	issue-5613-2
	[not available]	[not available]	[not available]	[not available]	[not available]	[not available]
	Inot available]	Inot available!	Paddle	3b4d9fe	[not available]	[not available]
	TestAgent	Okay	SdbAgent	3b4d9fe	[not available]	[not available]
Alan Alan	[not available]	[not available]	[not available]	[not available]		
			[not available]	[not available]		
Sand	Instrument State		[not available]	[not available]		
- Contraction -	xx01	Okay				
	Agent Alive Time	67344 s				
The operations T	Repository Revision	6a54d4e				
Log Messages						<u>.</u>

Take note of the colors you should mostly see greys (items that just aren't used in our setup) or greens. There may be a yellow or two but if there is any red there may be an issue.

#### Homing the Telescope

The telescope must be homed before it can be operated.

When PubSub loads it should already be on the *Axes* tab. If not click on it. Note that the axes are **Unhomed**.

Last

update: 2022/09/14 public:catalinas:lemmon:schulman\_32:startup\_procedure https://lavinia.as.arizona.edu/~tscopewiki/doku.php?id=public:catalinas:lemmon:schulman\_32:startup\_procedure&rev=1663191401 14:36

Mount	0	kay To	weekst /8 2015	04 III. 1940/01/56	
xes Command			ispenu ng 2010-	11-10 96102	
Agent Enable			Agent Disable		
Roll	Pitch				
Standby	Standby		Off		
Unhomed	Unhomed		UNKNOWN		
Pos  Vel	Pos Ovel		(8) Pos OVel		
0.0 deg	0.0	deg		de	
Slew	Slew		Slew		
Halt	Halt	Hal	t		
Home	Home		Home		
Park	Park			ĸ	
Unwrap	Unwrap				
Stop	Stop		Sto	P	
Stop Reset	Stop Rese	t	Stop R	eset	
Enable	Enable		Enable		
Disable	Disable		Disable		
Goto Pos L1	Goto Pos L1 Go		Goto Po	5 L 1	
Goto Neg L1	Goto Neg L1 Goto			eg L1	
Recover L2	Recover L	2	Recover L2		
Fault Reset	Fault Rese	t	Fault R	eset	
	Slew				
	Halt				
	Park				

Press the large HOME button (circled below) to move both axes simultaneously to the home position. See Telescope Orientation for the correct position.

Mount	Okay		
xes Command			
Agent Enable		Agent Disable	
Roll	Pitch	Rotator	
Standby	Standby	Off	
Homing	Homing	UNKNOWN	
Pos  Vel	Pos Ovel	Pos OVel	
0.0 deg	0.0 deg	0.0 deg	
Slew	Slew	Slew	
Halt	Halt	Halt	
Home	Home	Home	
Park	Park	Park	
Unwrap	Unwrap		
Stop	Stop	Stop	
Stop Reset	Stop Reset	Stop Reset	
Enable	Enable	Enable	
Disable	Disable	Disable	
Goto Pos L1	Goto Pos L1	Goto Pos L1	
Goto Neg L1	Goto Neg L1	Goto Neg L1	
Recover L2	Recover L2	Recover L2	
Fault Reset	Fault Reset	Fault Reset	
	Slew		
	Halt		
	Park		
	Park		

Once homed successfully the state field will briefly go to "stopped" and then finally "L1 Positive Limit" in both axes:

Last updai

update:	nublicicatalinasilommonischulman	22:startup procedure https://lavipia.as.arizona.or	lu/- tssopowiki/doku php?id=public;satalipas;lommon;ssbulmap	22:startup procedure&rev=1662101401
2022/09/14	public.catalillas.ieminon.schuman_		iu/~iscopewiki/uoku.php:iu=public.catalillas.lefillitofi.schullilati	_32.3taltup_procedule@iev=1003191401
14:36				

oent State	n Script S	equencer	Source	Tracking	Axes	Guide	Instrum
Nount			Ok	ay			
xes Command							
Ag	ent Enable	ļ	1		Agent Dis	able	
Roll		Pitch			Rotator		
Ökav		Okay		- 1	Off	_	_
United L1 Desit	un Limit	Ligited L	1 Docitivo	Linvit		A/5.1	
Pos Ovel	ve Limit		A	Carne .	Bear Ou	2005) 201	
0.0	deg	0.0	-	deg	0.0	9-1	deg
Slew			Slew			Slew	
Halt		Halt			Halt		
Home		Home			Home		
Park		-	Park		Park		
Unwra	p	-	Unwrap		Unwrab		
Stop			Stop		Stop		
Stop Re	set	S	top Reset		Stop Reset		
Enabl	e		Enable			Enable	
Disabl	e		Disable			Disable	
Goto Pos	L1	G	oto Pos L'		Goto Pos L1		
Goto Neg	L1	G	oto Neg L	1	G	sto Neg L	
Recover	L2	R	ecover L2		R	ecover L2	
Fault Re	set	F	ault Reset	:	R	ault Reset	
			Slew				
			Halt				
			Park				
			Home				
			Stop				

Now go to the *Source* tab and move the telescope out of the limits to a valid sky position. If the telescope is not going to be used immediately typically the telescope is sent to the Park position. Remember to stop the tracking loop if observing is not going to start. The Zenith position is inputted in the picture below.

tus ×					
← → C	18a/Source				Q☆ () :
Apps 🙀 PUBSUB! 🕒 APS: WebRelays 🕒 Power Outlets (Remo	Skycenter Trouble Re:	Mt. Lemmon SkyCent	NDOUTS 📑 Mt. Lemmon Obs	erva 🕘 Satellite page: RAP Re	SDO   Solar Dynamics >>
Tools R bas Chat (Alan) E General Gene			TUS	Alive 2016-1	1-01 23:25:14 UTC 18:48:46 LST
State Observation Script	Sequencer Source Tracking	Axes Guide Instrument Ins	View Spectrograph Calibrate	Focus Optical Tube Telescop	e Services 1 Telescope Services 2 +
Agent State		Source Selection		Refraction	
Astrometric	Okay	Astrometric Kernel State: Stopp	ed	Pressure:	mbar
Dalat		Known objects:	. 60	Humidity:	%
				Temperature:	°C
Point/Next S	art End	Source Name: none	Fetch Clear	Apply C	Override
Onto nearest pointing	tar Clear local offsets	Coordinates		Clear O	Iverride
Coto rearest portang.		Coordinate System: APP	ARENT_HA •	Tracking	
Source		Hour Angle: 0	h		
Name		Declination: 32	deg	Disable Roll Disable	e Pitch Enable Rotator
Right Ascension Source	NaN h	Space Motion		Stop Trac	king Loop
Declination Source	NaN deg	Where Where	a is it?	Rotator Mode	
Coordinate System	-	▶ When?	John	121/3	081
Equinox Source	NaN yr	Where w	vill it be?	Refraction	
Limit Expected	Horizon Limit	Clear local offsets	The second second	Manual Override	False
Limit Time Left	3.65 h	GO	Moon Flat	Air Temperature Value	0.0
Moon Zenith Distance	61.89 deg	3000		Barometric Pressure Value	0 mbar
Sun Zenith Distance	77.69 deg	Time		Humidity Value	0 %
		Local Apparent Sidereal Time	18:48:46 944 h	Wavelength	0.6000 um
telescope		Modified Julian Day	57693.9759 MJD	Guiding Wavelength	NaN um
Tracking In Tolerance	Out Of Tolerance	Julian Epoch	2016.8363 yr		
Air Mass	2.3429	TAI Minus UTC	36 s	Pointing Control	
Attude	25.15 deg	TT Minus TAI	32.1840 s	M1 and M2 Alignment	False Enable
Azimuth	1/9.23 deg	UT1 Minus UTC	-0.3238 s	Collimation Bolles Encodern	Ealeo
Hour Angle	-00:03:18:493 h			Roller Encoders	Enable Enable
Sun Senaration	122.20 dea	Orbital Element		Encoder Non-Linearity	Enable
Alas Moon Separation	47.44 dec	Source Orbital Element Scheme		Pointing Corrections	
	Livia wali	Source Orbital Element Argume	r NaN deg	Polar Motion X	0.1892 arcsec
Space Motion		Source Orbital Element Daily M	o NaN deg	Polar Motion Y	0.2811 arcsec
Send Source Space Motion Enabled	false	Source Orbital Element Eccentr	id NaN	Collimation Correction Enabled	False
Datum Tree Source Parallax	NaN arcsec	Source Orbital Element Epoch (	DINAN MJD	Collimation Correction Pitch	0 arcsec
File Operations Source Proper Motion Epoch	NaN yr	Source Orbital Element Epoch C		Collimation Correction Roll	0 arcsec
Log Messages Source Proper Motion Right As	ci NaN arcsec/vr	Source Orbital Element Longitue	olivan oeg	E.	*

Please see the Using the LCOGT GUI and Moving the Telescope section for more information.

### **Normal Startup Operations**

You have now successfully pulled the Schulman telescope out of Lightning Shutdown! Congrats. It is now time to start your normal program procedures to get everything ready for a SkyNight program or remote operation.

