

Normal Shutdown

1. Using GUI move the Telescope to stow position: Service Tab, click Stow, click GOTO directly below RELOAD
2. Close telescope mirror covers (in correct order - north first, then south)
3. Use remote paddle to line dome shutter with eastern wall.
4. Plug in shutter motor
5. Close shutter using shutter control box.
6. Shutdown TCS using "X" in upper right of GUI.
7. Shutdown TCS gui computer.
8. Turn off power to telescope drives at the Telescope power box
9. Switch dome control to local at the telescope power box.

From:

<https://lavinia.as.arizona.edu/~tscopewiki/> - **MOON**

Permanent link:

https://lavinia.as.arizona.edu/~tscopewiki/doku.php?id=21_inch:finishing_a_night_of_observing&rev=1403648285

Last update: **2014/06/24 15:18**

